

**DISK DRIVE COMPATIBILITY:** The following list of Peripheral Expansion Box (PBOX, PEB) compatible floppy disk drives was compiled by Glen Fredricks. It originally appeared in a 1987 issue of the Sheboygan Area 99er User Group's Newsletter.

<b>Manufacturer</b>	<b>Model</b>	<b>Height</b>	<b>Density</b>	<b>TPI</b>	<b>Bytes</b>	<b>Comments</b>
Canon	MDD 211	1/2	DS/DD	48	360K	Full power. Use only one in PEB
CDC	9409	Full	DS/DD	48	360K	Full power. Only one fits in PEB
CDC	9428	1/2	DS/DD	48	360K	Full power. Use only one in PEB
Epson	SD521	1/2	DS/DD	48	360K	2 OK in PEB
Hitachi	HFD505B	1/2	DS/DD	48	360K	2 OK in PEB
Matsushita	JA551	1/2	DS/DD	48	360K	Full power. Use only one in PEB
Matsushita	JA551N	1/2	DS/DD	48	360K	Full power. Use only one in PEB
Micropolis	115V	Full	DS/QD	96	720K	Of no use with a TI-99/4A
Mitsubishi	MT501A	1/2	DS/DD	40	360K	1/2 power. 2 are OK in PEB
Mitsubishi	M4851	1/2	DS/DD	48	360K	2 OK in PEB
Mitsubishi	M4853	1/2	DS/QD	96	720K	Of no use with TI-99/4A
MPI	B51	Full	SS/DD	48	90K	Full power. Sold in PEB
MPI	B52	Full	DS/DD	48	360K	Full power. One in PEB
MPI	B501C	1/2	DS/DD	48	360K	Full power. One in PEB
MPI	B502B	1/2L	DS/DD	48	360K	Full power. One in PEB
National	JA5512N	1/2	DS/DD	48	360K	Full power. One in PEB
Panasonic	JA5512N	1/2	DS/DD	48	360K	Full power. One in PEB
Qumetrack	142	1/2	DS/DD	48	360K	Full power. One in PEB
Qumetrack	142LX	1/2	DS/DD	48	360K	Full power. One in PEB
Qumetrack	542	Full	DS/DD	48	360K	Full power. One in PEB
Remex	RFD480	2/3	DS/DD	48	360K	Full power. One in PEB
Sanyo	FDA5200	1/2	DS/DD	48	360K	Made for IBM PCs
Sanyo	SM5480	1/2	DS/DD	48	360K	2 OK in PEB
Shugart	SA-400L	Full	SS/DD	48	90K	Full power. Sold in PEB
Shugart	SA-40L	Full	DS/DD	48	360K	Full power. One in PEB
Shugart	SA455-2	1/2	DS/DD	48	360K	2 OK in PEB
Shugart	SA465	1/2	DS/QD	96	720K	Of no use in TI. For IBM AT
Shugart	SA475	1/2	DS/QD	96	1.6M	Of no use in TI. For IBM AT
Siemens	FDD1005	Full	SS/DD	48	90K	Sold in PEB German made
Tandon	TM50-1	1/2	SS/DD	48	90K	Full power. Only one in PEB
Tandon	TM55-1	1/2	SS/DD	48	90K	Full power. Only one in PEB
Tandon	TM55-2	1/2	DS/DD	48	360K	Full power. Only one in PEB
Tandon	TM55-4	1/2	DS/QD	96	720K	Of no use in TI PEB
Tandon	TM65-2L	1/2	DS/QD	96	1.6M	Of no use in TI PEB
Tandon	TM100-1	Full	SS/DD	48	180K	Full power. Only one in PEB
Tandon	TM100-2	Full	DS/DD	48	380K	Full power. Only one in PEB
Tandon	TM100-4	Full	DS/QD	48	720K	Of no use in TI PEB. Made for IBM
Teac	FD-55A	1/2	SS/DD	48	180K	2 OK in PEB
Teac	FD-55B	1/2	DS/DD	48	360K	2 OK in PEB
Teac	FD-55BV	1/2	DS/DD	48	360K	Of no use in TI PEB. Made for IBM
Teac	FD-55E	1/2	SS/QD	96	500K	Of no use in TI PEB
Teac	FD-55F	1/2	DS/QD	96	1.0M	Of no use in TI PEB
Teac	FD-55GF	1/2	DS/QD	96	1.2M	Of no use in TI PEB. Made for IBM AT
TEC	FB503	1/2	SS/DD	48	90K	2 OK in PEB
Toshiba	5401	Full	SS/SD	48	90K	Full power. One in PEB
Toshiba	ND-04D	1/2	DS/DD	48	360K	2 OK in PEB
Toshiba	ND-040T	1/2	DS/DD	48	360K	Of no use in TI PEB. Made for IBM
Y.E. Data	YD580	1/2	DS/QD	96	720K	Of no use with TI-99/4A